











## Gestures

The HOT Watch detects hand gestures using a 6-axis accelerometer and gyroscope. The gyroscope is switched Off by default to save battery power. It is


Feature	Action	Gesture Detail
LED Backlight		
Voice Response		







global notifications. The notification size limit is 380 characters for Android. The user can respond to SMS notifications from the watch.

In iPhone, the HOTWatch receives notifications via Bluetooth Low Energy (BLE) with GATT-ANCS profile. Once the BLE-GATT-ANCS is connected, these

The notification size limit is 90 characters for iPhone due to BLE limitation.

To connect to BLE, tap on the tick adjacent to BLE, and make sure the HOTWatch Application is running in the foreground. Accept BLE pair request from the HOTWatch Application.

To connect to MAP, tap on the tick adjacent to SMS. In Phone Bluetooth menu, navigate to the connected device info and enable

 ICON1

 ICON2

 ICON3

 ICON4






The icons in Sections 1 are pre-loaded with watch faces that are optimized to be energy efficient. Six Watch faces are available in Section 1. The watch faces have a Time and Date display. The seconds' hand (or seconds

(6AM-6PM) or night (6PM to 6AM). The second city is customizable from the









—

—

1













4A

4

















